

Showing the video stream of IP BOLD's camera on a Snom IP video phone

Your Snom IP phone can show the video of your IP Bold video doorbell.

Prerequisites:

- Tested with D375 (FW 8.9.3.15), D765 (FW 8.7.5.35)
- Snom phone must have a graphic display (tested with 375, 765)
- IP BOLD doorstation must be an extension of the same PBX where the snom phone is registered

How to:

- Access the web user interface of your Snom phone.
- Select "directory"
- Create a new entry as follows:

Directory snom

Number of the IP Bold extension

Operation
Home
Directory

Setup
Preferences
Speed Dial
Function Keys
Identity 1
Identity 2
Identity 3
Identity 4
Identity 5
Identity 6
Identity 7
Identity 8
Identity 9
Identity 10
Identity 11
Identity 12
Action URL Settings
Advanced
Certificates
Software Update

Status
System Information

Directory

Name:	Number:	Contact Type:	Outgoing Identity:	Edit	Delete
-------	---------	---------------	--------------------	------	--------

Add or Edit Entry:

Number:

Number Type:

Contact Type:

Outgoing Identity:

Group:

Title:

Organization:

Email:

Note:

Photo:

Action-Url:

Nickname:

First Name:

Family Name:

BirthDay:

Favorite:

IP of IP bold

Add/Edit

When a call from extension 51 (as in this example) arrives, then the content of the field "Action-Url" will be executed, which will show the current video of the IP BOLD doorstation.

It is also possible to add the same URL in one of the fields of function key, so you can open up the video of IP BOLD without having received a call:

Context	Type	Number	Short Text	
Active	Action URL	http://172.16.1.201/snom01	Doorbell	P1
Active	Line			P2